

**Table 4-2.** System Error Codes (Continued)

<b>Code</b>	<b>Technical Error Condition</b>
289	Sensor Private Label/Host Sensor Key incompatible; will not operate sensor
512	SpO2 back end reports internal software consistency check failed
513	SpO2 back end reports software functions executed before initialization completed
514	SpO2 back end reports internal memory buffer overflow
516	SpO2 back end ROM / code integrity error
517	SpO2 back end RAM error
518	SpO2 back end reports internal software consistency check failed
519	SpO2 back end reports a state machine is in an unexpected state
520	SpO2 back end reports memory corruption detected
521	SpO2 back end reports spurious interrupt detected
522	SpO2 back end reports unable to issue commands to SpO2 front end
523	SpO2 back end reports unable to write to external Flash
524	SpO2 back end reports that communication with SpO2 front end lost
525	SpO2 back end reports internal register modified from expected value
701	Flash writing transaction error
901	SpO2 module communication error / Setting value mismatch error between host and SpO2 module
902	Program memory error
903	RAM error
904	PSRAM error
905	Sub MCU communication error
907	RTC error
908	Serial flash memory error
909	Internal voltage error
910	Sound / Speaker error
912	LCD error
913	Button error
920	Abnormally shut down last time